



Drawings available for maximum P.C Board size for top and bottom

Dimensions:  
 mm  
 [inches]

Enclosures can be Factory Modified (Milling, Drilling, Printing etc.)  
 Contact Factory (modshop@hammfg.com) for quotes  
 Solid models of this enclosure available in .stp or .x\_t  
 (Part number and text placement/orientation on our products are subject to change, we do not recommend using them as a locating reference for modification purposes)

NOTE	
Purchased assembly includes top and bottom cover, 1 removable panel, battery door, battery spring clips (4 pcs), 9V adapter (1 pcs) and 4 cover screws (M3-0.5 x 18mm). M3 Brass inserts are installed for cover screws.	
Enclosure molded from FR ABS (UL94-V0).	
<b>Recommended Cover Screw Torque - 43-50 ozf.in (30-35cN-m)</b>	

PART NUMBERS	
1599TABSBAT Enclosure	
Black Enclosure	1599TABSBKBAT
Grey Enclosure	1599TABSGYBAT
ACCESSORIES	
Replacement Cover Screws [M3-0.5 x 18mm] (Pkg 100)	1594MS100 (Silver) 1594MS100BK (Black)
P.C. Board Screws (#4 x 1/4" Self Tapping)	1593ATS50 (Pkg 50) 1593ATS100 (Pkg 100)
1599TABS End Panel (Single Panel)	1599TABSPLBK-B (Black) 1599TABSPLGY-B (Grey)
9V Battery Kit	53BATCLIP9V-B
AA Battery Clip Kit (4 positive and 4 Negative)	1553HDR-BKIT

**HAMMOND MANUFACTURING**  
**1599TABSBAT**  
 www.hammondmfg.com